

# VHF SINGLE CHANNEL SYSTEM



## WR-58V/SERIES >>> PROFESSIONAL WIRELESS MICROPHONE SYSTEM

### WR-58V



### HT-68V/HT-218



### PT-68V



#### RECEIVER SPECIFICATIONS

Channel Frequency: 170–260MHz  
Sensitivity: -95dBm (S/N:12dB)  
RF Image Rejection:-75dB  
Audio Dynamic Range:95dB T.H.D.:<1%  
Frequency stability:±0.002%  
S/N Ratio: >70dB  
Neighboring Channel / Interference: >70dB  
Frequency Response: 50Hz~15KHz±3dB  
Power Requirements:13-15V DC nominal 150mA  
Dimensions:16.9x12x3.7cm

#### HANDHELD TRANSMITTER SPECIFICATIONS


Carrier Frequency:170–260MHz  
RF Power Output: >13dBm  
Modulation Degree: >30KHz  
Power Current: <110mA  
Frequency Stability: ±0.002%  
Harmonic at Higher Degree: <60dB  
Modulation pattern: FM  
Power Requirements:3V (2x1.5V AA)  
HT-68V Dimensions:23.8x5x5cm  
HT-218 Dimensions:25x5.1x5.1cm

#### BODYPACK TRANSMITTER SPECIFICATIONS

Carrier Frequency:170–260MHz  
RF Power Output: >13dBm  
Modulation Degree: >30KHz  
Power Current: <110mA  
Frequency Stability: ±0.002%  
Harmonic at Higher Degree: <60dB  
Modulation pattern: FM  
Power Requirements:3V (2x1.5V AA)  
Dimensions:10X6.5X3cm



PT-68V  
BODYPACK TRANSMITTER



Top View



HT-68V  
HANDHELD TRANSMITTER

HT-218  
HANDHELD TRANSMITTER



WR-58V  
SINGLE CHANNEL RECEIVER



Rear Panel

#### HANDHELD



#### LAVALIER



#### HEADWORN



#### GUITAR/BASS

