


PLL & UHF ANTENNA DIVERSITY DUAL CHANNEL SYSTEM

SYSTEM FEATURES

- ※ 2x100 Selectable UHF channel.
- ※ Adopt the PLL-Synthesized control technic.
- ※ Antenna diversity dual channel operation.
- ※ LED information display
- ※ Double squelch operation circuit, higher efficient and much more steady.
- ※ Adjustable antenna, enhance receiving signal function.
- ※ Receiver with auto-searching function.
- ※ Install with surface acoustic filter avoiding interruption from other signal and noise
- ※ Balanced XLR and unbalanced 1/4" outputs.



PT-500 BODYPACK TRANSMITTER



Top View

WR-520 ANTENNA DIVERSITY RECEIVER



19-inch Audio equipment rack



Rear Panel

HT-500 HANDHELD TRANSMITTER

PLL 100CH

WR-520 SERIES >>>

PROFESSIONAL WIRELESS MICROPHONE SYSTEM

WR-520



RECEIVER SPECIFICATIONS

Frequency Range:460-970MHz
 Power Requirement:13-15V DC nominal 800mA
 S/N Ratio:>90dB
 RF Image Spurious Rejection:>80dB
 Border Upon Channel Rejection:>80dB
 Receiving Sensitivity:>-105dBm(S/N:-12dB 15KHz)
 Dimensions:20x17.5x4.4cm

HT-500



HANDHELD TRANSMITTER SPECIFICATIONS

Frequency Range:460-970MHz
 RF Output:10dBm
 Modulation Type:FM
 Max Deviation:±68KHz
 Spurious Emission:>55dBc
 Power Requirements:3V (2x1.5V AA)
 Dimensions:24x5x5cm

PT-500



BODYPACK TRANSMITTER SPECIFICATIONS

Frequency Range:460-970MHz
 RF Output:10dBm
 Modulation Type:FM
 Max Deviation:±68KHz
 Spurious Emission:>55dBc
 Power Requirements:3V(2x1.5V AA)
 Dimensions:8.5x7x2.5cm

HANDHELD



LAVALIER



HEADWORN



GUITAR/BASS



DUAL CHANNEL COMBO

