

VHF SINGLE CHANNEL SYSTEM



WR-68V SERIES >>>

PROFESSIONAL WIRELESS MICROPHONE SYSTEM

WR-68V



HT-68V/HT-218



PT-68V



RECEIVER SPECIFICATIONS

Channel Frequency: 170~260MHz
 Sensitivity: -95dBm (S/N:12dB)
 RF Image Rejection:-75dB
 Audio Dynamic Range:95dB T.H.D.: <1%
 Frequency stability: ±0.002%
 S/N Ratio: >70dB
 Neighboring Channel / Interference: >70dB
 Frequency Response: 50Hz~15KHz ±3dB
 Power Requirements:13-15V DC nominal 150mA
 Dimensions:17.5X13.5X4.3cm

HANDHELD TRANSMITTER SPECIFICATIONS

Carrier Frequency:170~260MHz
 RF Power Output: >13dBm
 Modulation Degree: >30KHz
 Power Current: <110mA
 Frequency stability: ±0.002%
 Harmonic at Higher Degree: <60dB
 Modulation pattern: FM
 Power Requirements:3V (2x1.5V AA)
 HT-68V Dimensions:23.8x5x5cm
 HT-218 Dimensions:25x5.1x5.1cm

BODYPACK TRANSMITTER SPECIFICATIONS

Carrier Frequency:170~260MHz
 RF Power Output: >13dBm
 Modulation Degree: >30KHz
 Power Current: <110mA
 Frequency Stability: ±0.002%
 Harmonic at Higher Degree: <60dB
 Modulation pattern: FM
 Power Requirements:3V (2x1.5V AA)
 Dimensions:10X6.5X3cm



1 WR-68V SINGLE CHANNEL RECEIVER

1 PT-68V BODYPACK TRANSMITTER

1 HT-68V HANDHELD TRANSMITTER

1 HT-218 HANDHELD TRANSMITTER

HANDHELD



LAVALIER



HEADWORN



GUITAR/BASS

